



TheGreenBow IPSec VPN Client Configuration Guide

- Huawei Symantec
Secoway SVN2260

WebSite: <http://www.thegreenbow.com>

Contact: support@thegreenbow.com

Configuration Guide written by:

Company:

Table of contents

1	Introduction	3
1.1	Goal of this document	3
1.2	VPN Network topology	3
1.3	Huawei Symantec Secoway SVN2260 Restrictions.....	3
1.4	Huawei Symantec Secoway SVN2260 VPN Gateway.....	3
1.5	Huawei Symantec Secoway SVN2260 VPN Gateway product info	3
2	Huawei Symantec Secoway SVN2260 VPN configuration	5
2.1	Setup SVN2260 for VPN tunneling	5
3	TheGreenBow IPSec VPN Client configuration	7
3.1	VPN Client Phase 1 (IKE) Configuration	7
3.2	VPN Client Phase 2 (IPSec) Configuration	8
3.3	Open IPSec VPN tunnels.....	8
4	Tools in case of trouble.....	9
4.1	A good network analyser: Wireshark.....	9
5	VPN IPSec Troubleshooting	10
5.1	« PAYLOAD MALFORMED » error (wrong Phase 1 [SA])	10
5.2	« INVALID COOKIE » error.....	10
5.3	« no keystate » error	10
5.4	« received remote ID other than expected » error.....	10
5.5	« NO PROPOSAL CHOSEN » error	11
5.6	« INVALID ID INFORMATION » error	11
5.7	I clicked on "Open tunnel", but nothing happens.....	11
5.8	The VPN tunnel is up but I can't ping !.....	11
6	Contacts.....	13


1 Introduction

1.1 Goal of this document

This configuration guide describes how to configure TheGreenBow IPsec VPN Client software with a Huawei Symantec Secoway SVN2260 VPN gateway to establish VPN connections for remote access to corporate network

1.2 VPN Network topology

In our VPN network example (diagram hereafter), we will connect TheGreenBow IPsec VPN Client software to the LAN behind the Huawei Symantec Secoway SVN2260 gateway. The VPN client is connected to the Internet with a DSL connection or through a LAN. All the addresses in this document are given for example purpose.



1.3 Huawei Symantec Secoway SVN2260 Restrictions

No known restrictions.

1.4 Huawei Symantec Secoway SVN2260 VPN Gateway

Our tests and VPN configuration have been conducted with Huawei Symantec Secoway SVN2260 firmware release V200R001c00SPC200.

1.5 Huawei Symantec Secoway SVN2260 VPN Gateway product info

It is critical that users find all necessary information about Huawei Symantec Secoway SVN2260 VPN Gateway. All product info, User Guide and knowledge base for the Huawei Symantec Secoway SVN2260 VPN Gateway can be found on the Huawei Symantec Secoway SVN2260 website:

http://www.huaweisymantec.com/en/Product_Solution/Products/Security/SVN/SVN/Secospace_SVN3000/

Doc.Ref	tgbvpn_ug-Huawei-Secoway-SVN2260-en
Doc.Version	Mar 2012
VPN Version	5.1

Huawei Symantec Secoway SVN2260 Product page	http://www.huaweisymantec.com/en/Product_Solution/Products/Security/SVN/SVN/Secospace_SVN3000/
Huawei Symantec Secoway SVN2260 User Guide	http://www.huaweisymantec.com/en/Product_Solution/Products/Security/SVN/SVN/Secospace_SVN3000/
Huawei Symantec Secoway SVN2260 FAQ/Knowledge Base	http://www.huaweisymantec.com/en/Product_Solution/Products/Security/SVN/SVN/Secospace_SVN3000/


2 Huawei Symantec Secoway SVN2260 VPN configuration

This section describes how to build an IPSec VPN configuration with your Huawei Symantec Secoway SVN2260 VPN gateway.


Once connected to your Huawei Symantec Secoway SVN2260 VPN gateway, you must select "VPN" and "IKE Negotiation" tabs.

2.1 Setup SVN2260 for VPN tunneling


Click on Phase1 to create a tunnel.



At the phase 1, chose "Main Mode" as the Negotiation Mode, enter your Pre-Shared Key and activate NAT Traversal.




In VPN > IPsec > IKE Negotiation > Add the phase 2 and chose Tunnel Mode as the Encapsulation Mode, DH-Group2 as the PFS.



In VPN > IPsec > Apply IPsec Policy, create an IPsec Rule with IP and Subnet (Wildcard mask) to be reached by VPN Client.

Destination address is the VPN Client virtual IP address.




3 TheGreenBow IPsec VPN Client configuration

This section describes the required configuration to connect to a Huawei Symantec Secoway SVN2260 VPN gateway via VPN connections.

To download the latest release of TheGreenBow IPsec VPN Client software, please go to:

http://www.thegreenbow.com/vpn_down.html


3.1 VPN Client Phase 1 (IKE) Configuration



Phase 1 configuration

This configuration is one example of what can be accomplished in term of User Authentication. You may want to refer to either the Huawei Symantec Secoway SVN2260 gateway user guide or TheGreenBow IPsec VPN Client software User Guide for more details on User Authentication options.

3.2 VPN Client Phase 2 (IPSec) Configuration



Phase 2 Configuration

3.3 Open IPsec VPN tunnels

Once both Huawei Symantec Secoway SVN2260 gateway and TheGreenBow IPsec VPN Client software have been configured accordingly, you are ready to open VPN tunnels. First make sure you enable your firewall with IPsec traffic.

1. Click on "Save & Apply" to take into account all modifications we've made on your VPN Client configuration
2. Click on "Open Tunnel", or generate traffic that will automatically open a secure IPsec VPN Tunnel (e.g. ping, IE browser)
3. Select "Connections" to see opened VPN Tunnels
4. Select "Console" if you want to access to the IPsec VPN logs and adjust filters to display less IPsec messaging. The following example shows a successful connection between TheGreenBow IPsec VPN Client and a Huawei Symantec Secoway SVN2260 VPN gateway.

```

20120227 17:14:55:639 Default (SA Gateway-P1) SEND phase 1 Main Mode [SA] [VID] [VID] [VID] [VID] [VID]
20120227 17:14:56:516 Default (SA Gateway-P1) RECV phase 1 Main Mode [SA] [VID] [VID] [VID]
20120227 17:14:56:580 Default (SA Gateway-P1) SEND phase 1 Main Mode [KEY_EXCH] [NONCE] [NAT_D] [NAT_D]
20120227 17:14:57:574 Default (SA Gateway-P1) RECV phase 1 Main Mode [KEY_EXCH] [NONCE] [NAT_D] [NAT_D]
20120227 17:14:57:710 Default (SA Gateway-P1) SEND phase 1 Main Mode [HASH] [ID]
20120227 17:14:58:528 Default (SA Gateway-P1) RECV phase 1 Main Mode [HASH] [ID]
20120227 17:14:58:574 Default phase 1 done: initiator id 192.168.1.71, responder id 192.168.20.100
20120227 17:14:58:736 Default (SA Gateway-Tunnel-P2) SEND phase 2 Quick Mode [HASH] [SA] [KEY_EXCH] [NONCE] [ID] [ID]
20120227 17:14:59:914 Default (SA Gateway-Tunnel-P2) RECV phase 2 Quick Mode [HASH] [SA] [KEY_EXCH] [NONCE] [ID] [ID] [NOTIFY]
20120227 17:15:00:007 Default (SA Gateway-Tunnel-P2) SEND phase 2 Quick Mode [HASH]
20120227 17:15:01:480 Default (SA Gateway-Tunnel-P2) [VirtualIf] Virtual Interface properly configured for instance 1 and IfIndex 20.
    
```


4 Tools in case of trouble

Configuring an IPSec VPN tunnel can be a hard task. One missing parameter can prevent a VPN connection from being established. Some tools are available to find source of troubles during a VPN establishment.

4.1 A good network analyser: Wireshark

Wireshark is a free software that can be used for packet and traffic analysis. It shows IP or TCP packets received on a network card. This tool is available on website <http://www.wireshark.org>. It can be used to follow protocol exchange between two devices. For installation and use details, read its specific documentation (<http://www.wireshark.org/docs/>).

No. .	Time	Source	Destination	Protocol	Info
1	0.000000	192.168.1.3	192.168.1.2	ISAKMP	Identity Protection (Main Mode)
2	0.153567	192.168.1.2	192.168.1.3	ISAKMP	Identity Protection (Main Mode)
3	0.205363	192.168.1.3	192.168.1.2	ISAKMP	Identity Protection (Main Mode)
4	0.257505	192.168.1.2	192.168.1.3	ISAKMP	Identity Protection (Main Mode)
5	0.300882	192.168.1.3	192.168.1.2	ISAKMP	Identity Protection (Main Mode)
6	0.310186	192.168.1.2	192.168.1.3	ISAKMP	Identity Protection (Main Mode)
7	0.313742	192.168.1.3	192.168.1.2	ISAKMP	Quick Mode
8	0.321913	192.168.1.2	192.168.1.3	ISAKMP	Quick Mode
9	0.323741	192.168.1.3	192.168.1.2	ISAKMP	Quick Mode
10	0.334980	192.168.1.2	192.168.1.3	ISAKMP	Quick Mode
11	0.691160	192.168.1.3	192.168.1.2	ESP	ESP (SPI=0x919bfabc)
12	1.692568	192.168.1.3	192.168.1.2	ESP	ESP (SPI=0x919bfabc)
13	1.693164	192.168.1.2	192.168.1.3	ESP	ESP (SPI=0x53a5925e)
14	2.693600	192.168.1.3	192.168.1.2	ESP	ESP (SPI=0x919bfabc)
15	2.694026	192.168.1.2	192.168.1.3	ESP	ESP (SPI=0x53a5925e)

Frame 1 (142 bytes on wire, 142 bytes captured)
 Ethernet II, Src: 00:50:04:ad:f2:73, Dst: 00:10:b5:07:2f:ff

5 VPN IPSec Troubleshooting

5.1 « PAYLOAD MALFORMED » error (wrong Phase 1 [SA])

```
114920 Default (SA CNXVPN1-P1) SEND phase 1 Main Mode [SA][VID]
114920 Default (SA CNXVPN1-P1) RECV phase 1 Main Mode [NOTIFY]
114920 Default exchange_run: exchange_validate failed
114920 Default dropped message from 195.100.205.114 port 500 due to notification
type PAYLOAD_MALFORMED
114920 Default SEND Informational [NOTIFY] with PAYLOAD_MALFORMED error
```

If you have an « PAYLOAD MALFORMED » error you might have a wrong Phase 1 [SA], check if the encryption algorithms are the same on each side of the VPN tunnel.

5.2 « INVALID COOKIE » error

```
115933 Default message_rcv: invalid cookie(s) 5918ca0c2634288f 7364e3e486e49105
115933 Default dropped message from 195.100.205.114 port 500 due to notification
type INVALID_COOKIE
115933 Default SEND Informational [NOTIFY] with INVALID_COOKIE error
```

If you have an « INVALID COOKIE » error, it means that one of the endpoint is using a SA that is no more in use. Reset the VPN connection on each side.

5.3 « no keystate » error

```
115315 Default (SA CNXVPN1-P1) SEND phase 1 Main Mode [SA][VID]
115317 Default (SA CNXVPN1-P1) RECV phase 1 Main Mode [SA][VID]
115317 Default (SA CNXVPN1-P1) SEND phase 1 Main Mode [KEY][NONCE]
115319 Default (SA CNXVPN1-P1) RECV phase 1 Main Mode [KEY][NONCE]
115319 Default (SA CNXVPN1-P1) SEND phase 1 Main Mode [ID][HASH][NOTIFY]
115319 Default ipsec_get_keystate: no keystate in ISAKMP SA 00B57C50
```

Check if the preshared key is correct or if the local ID is correct (see « Advanced » button). You should have more information in the remote endpoint logs.

5.4 « received remote ID other than expected » error

```
120348 Default (SA CNXVPN1-P1) SEND phase 1 Main Mode [SA][VID]
120349 Default (SA CNXVPN1-P1) RECV phase 1 Main Mode [SA][VID]
120349 Default (SA CNXVPN1-P1) SEND phase 1 Main Mode [KEY][NONCE]
120351 Default (SA CNXVPN1-P1) RECV phase 1 Main Mode [KEY][NONCE]
120351 Default (SA CNXVPN1-P1) SEND phase 1 Main Mode [ID][HASH][NOTIFY]
120351 Default (SA CNXVPN1-P1) RECV phase 1 Main Mode [ID][HASH][NOTIFY]
120351 Default ike_phase_1_rcv_ID: received remote ID other than expected
support@thegreenbow.fr
```

The « Remote ID » value (see « Advanced » Button) does not match what the remote endpoint is expected.

5.5 « NO PROPOSAL CHOSEN » error

```

115911 Default (SA CNXVPN1-P1) SEND phase 1 Main Mode [SA][VID]
115913 Default (SA CNXVPN1-P1) RECV phase 1 Main Mode [SA][VID]
115913 Default (SA CNXVPN1-P1) SEND phase 1 Main Mode [KEY][NONCE]
115915 Default (SA CNXVPN1-P1) RECV phase 1 Main Mode [KEY][NONCE]
115915 Default (SA CNXVPN1-P1) SEND phase 1 Main Mode [ID][HASH][NOTIFY]
115915 Default (SA CNXVPN1-P1) RECV phase 1 Main Mode [ID][HASH][NOTIFY]
115915 Default phase 1 done: initiator id c364cd70: 195.100.205.112, responder id
c364cd72: 195.100.205.114, src: 195.100.205.112 dst: 195.100.205.114
115915 Default (SA CNXVPN1-CNXVPN1-P2) SEND phase 2 Quick Mode
[SA][KEY][ID][HASH][NONCE]
115915 Default RECV Informational [HASH][NOTIFY] with NO_PROPOSAL_CHOSEN error
115915 Default RECV Informational [HASH][DEL]
115915 Default CNXVPN1-P1 deleted

```

If you have an « NO PROPOSAL CHOSEN » error, check that the « Phase 2 » encryption algorithms are the same on each side of the VPN Tunnel.

Check « Phase 1 » algorithms if you have this:

```

115911 Default (SA CNXVPN1-P1) SEND phase 1 Main Mode [SA][VID]
115911 Default RECV Informational [NOTIFY] with NO_PROPOSAL_CHOSEN error

```

5.6 « INVALID ID INFORMATION » error

```

122623 Default (SA CNXVPN1-P1) SEND phase 1 Main Mode [SA][VID]
122625 Default (SA CNXVPN1-P1) RECV phase 1 Main Mode [SA][VID]
122625 Default (SA CNXVPN1-P1) SEND phase 1 Main Mode [KEY][NONCE]
122626 Default (SA CNXVPN1-P1) RECV phase 1 Main Mode [KEY][NONCE]
122626 Default (SA CNXVPN1-P1) SEND phase 1 Main Mode [ID][HASH][NOTIFY]
122626 Default (SA CNXVPN1-P1) RECV phase 1 Main Mode [ID][HASH][NOTIFY]
122626 Default phase 1 done: initiator id c364cd70: 195.100.205.112, responder id
c364cd72: 195.100.205.114, src: 195.100.205.112 dst: 195.100.205.114
122626 Default (SA CNXVPN1-CNXVPN1-P2) SEND phase 2 Quick Mode
[SA][KEY][ID][HASH][NONCE]
122626 Default RECV Informational [HASH][NOTIFY] with INVALID_ID_INFORMATION error
122626 Default RECV Informational [HASH][DEL]
122626 Default CNXVPN1-P1 deleted

```

If you have an « INVALID ID INFORMATION » error, check if « Phase 2 » ID (local address and network address) is correct and match what is expected by the remote endpoint.

Check also ID type ("Subnet address" and "Single address"). If network mask is not check, you are using a IPV4_ADDR type (and not a IPV4_SUBNET type).

5.7 I clicked on "Open tunnel", but nothing happens.

Read logs of each VPN tunnel endpoint. IKE requests can be dropped by firewalls. An IPSec Client uses UDP port 500 and protocol ESP (protocol 50).


5.8 The VPN tunnel is up but I can't ping !

If the VPN tunnel is up, but you still cannot ping the remote LAN, here are a few guidelines:

- Check Phase 2 settings: VPN Client address and Remote LAN address. Usually, VPN Client IP address should not belong to the remote LAN subnet
- Once VPN tunnel is up, packets are sent with ESP protocol. This protocol can be blocked by firewall. Check that every device between the client and the VPN server does accept ESP
- Check your VPN server logs. Packets can be dropped by one of its firewall rules.
- Check your ISP support ESP

Doc.Ref	tgbvpn_ug-Huawei-Secoway-SVN2260-en
Doc.Version	Mar 2012
VPN Version	5.1

- If you still cannot ping, follow ICMP traffic on VPN server LAN interface and on LAN computer interface (with Wireshark for example). You will have an indication that encryption works.
- Check the "default gateway" value in VPN Server LAN. A target on your remote LAN can receive pings but does not answer because there is a no "Default gateway" setting.
- You cannot access to the computers in the LAN by their name. You must specify their IP address inside the LAN.
- We recommend you to install Wireshark (<http://www.wireshark.org>) on one of your target computer. You can check that your pings arrive inside the LAN.

	Doc.Ref	tgbvpn_ug-Huawei-Secoway-SVN2260-en
	Doc.Version	Mar 2012
	VPN Version	5.1

6 Contacts

News and updates on TheGreenBow web site: <http://www.thegreenbow.com>

Technical support by email at support@thegreenbow.com

Sales contacts by email at sales@thegreenbow.com

Secure, Strong, Simple.

TheGreenBow Security Software